

LCD PULSE COUNTER, CODIX 130

6.130.012.862

CODIX 130 LCD COUNTER 4-30 V DC

- Battery powered
- Adding or subtracting
- 8 Digit display
- PNP/NPN input



PRODUCT DESCRIPTION

Pulse counter for adding up pulses. Runs on a lithium battery with a service life of eight years. Two different types of counter input, either a low frequency counter (30 Hz) for contact / NPN input, or a high frequency counter (12 kHz) for 4-30 V DC PNP input. You can choose whether you want an external reset or a reset at the front of the counter. The reset button can also be locked. This is done at the coupling on the back of the counter. The counter is available with background lighting (not kept in stock). The counter comes with clamps, gaskets and separate front frames to fit 25x50 mm panel holes. One for screw fitting and one without.

