OEM Automatic Ltd
Address: Whiteacres, Whetstone Leicester, LE8 6ZG
0116 284 9900 | Orders@oem.co.uk | www.oem.co.uk

LCD PRESET COUNTER, CODIX 901

6.901.010.820
901 LCD PRESET COUNTER



- Battery powered
- 1 Preset - pulse, time
- 2 line, 6 and 7 digit display
- 30Hz Max. count frequency

PRODUCT DESCRIPTION

A simple preset counter as a direct replacement for the electromechanical counters for addition or subtraction, with one preset. This counter is run on two lithium batteries, which can be replaced. 6-digit LCD display, with a digit height of 7 mm and 4 mm for the preset value. The functions and preset value are programmed using the buttons at the front of the counter. The preset is set using one button for every digit. This counter is reset manually, electrically or automatically. You can also block the buttons at the front. The counter comes with clamps and separate front frames to fit both 45x45 mm and 50x50 mm panel holes.

Pulse counter


For counting and adding pulses:
The counter function is selected during programming:


- Addition or subtraction
- Relay outputs closing or breaking
- Manual or automatic reset
- The relay's pulse time at automatic reset
- Position of the decimal point (optical assistance only)


TECHNICAL DATA


Count rate	25
Input impedance, typ	110 kΩ
Input voltage max	250
IP class	IP65
Panel size	48x48 mm
Pulse input min	50
Storage temperature max	60 °C
Storage temperature min	-25 °C
Temperature operational max	50 °C
Temperature operational min	-10 °C

Weight	80 g


12 - 250
VAC/VDC
Key lock
Reset
Count
1 2 3 4 5 6 7
Relaycontact


Frontramarna följer med räknaren
45
45
50
50
50
63


12 - 250
VAC/VDC
Key lock
Reset
Count
1 2 3 4 5 6 7
Relaycontact


Frontramarna följer med räknaren
45
45
50
50
50
63