



SUCO 0530 ELECTRONIC PRESSURE SWITCH

053025103B004
PNP output (High Side), NO, 0-25 Bar, G 1/4 – DIN
3852-A, Bayonet ISO 15170-A1-4.1

- One switching output
- Stainless steel & titanium wetted parts
- Silicon-on-sapphire technology
- Factory set



PRODUCT DESCRIPTION

The Suco high performance series of electronic pressure switches offers outstanding overpressure protection (up to 4x), long service life even under high pressure change rates whilst giving very low temperature error and excellent long-term stability. Using Silicon-on-sapphire technology for high reliability, EMC compatibility and accuracy there are five standard pressure ranges starting at 0-10 bar all the way up to 0-600 bar and a hysteresis of 0.2%-99.8%. Output option of PNP or NPN and the choice of normally open or normally closed with one switching output factory set (unadjustable by the user). The wetted parts are made of stainless steel and titanium in an all welded design ensuring excellent media compatibility with seven standard electrical connection options including Deutsch, DIN and M12 combined with eight standard thread type options.

Customer specific solutions are also available on request.

Application examples

- Automotive
- Braking systems
- Medical
- Mobile hydraulics
- Off highway
- Off-shore
- Rail

TECHNICAL DATA

GENERAL DATA

Adjustment range max	25 bar
Adjustment range min	0 bar
Process connection	G1/4
Function	Normally open (SPST)

Output	PNP
Burst pressure	200 bar
Pressure max	100 bar

TEMPERATURE & MATERIALS DATA

Temperature of media from	-40 °C
Temperature of media to	125 °C
Temperature ambient from	-40 °C
Temperature ambient to	100 °C
Material of body	Stainless steel 1.4305
Material of wetted parts	Stainless steel 1.4305, Titanium

ADDITIONAL DATA

Supply voltage dc max	32 V DC
Supply voltage dc min	9.6 V DC
Pressure rise	≤ 5,000 bar/s
Switching time	< 2 ms
Switching point adjustment range	2 ... 100 % of the nominal pressure range Full Scale (FS), programmable at factory
Weight	80 g

SAFETY & APPROVALS

IP class	IP67, IP6K9K
Hysteresis	2..99.8% of nominal pressure range (full scale), programmable at factory
Shock resistance	500m / s ² ; 11 ms half sine wave; DIN EN 60068-2-27
Vibration resistance	20g: 4..2000 Hz sine wave, DIN EN 60068-2-6
EMC	EMC 2014/30/EU, EN 61000-6-2:2005, EN 61000-6-3:2007
Accuracy	±0.5 % of adjustment range (Full scale) at room temperature
Long term stability	±0.1 % of adjustment range (full scale) per year
Mechanical life expectancy	10,000,000 switching cycles at rise rates to 5,000 bar/s nominal pressure
Repeatability	±0.1 % full scale



See 221

Connection diagrams

Up to 100 VAC



For permanent operation on each connector

100 VAC 100 Hz



For permanent operation on each connector

Technical modifications and errors excepted.

EN 175301-803-A	M 12 - DIN EN 61076-2-101 A	ISO 15176-A1-4-1	AMP Superseal																																								
<table><tr><th>Pin</th><th>Assignment</th></tr><tr><td>1</td><td>Chassis</td></tr><tr><td>2</td><td>Chassis</td></tr><tr><td>3</td><td>Chassis</td></tr><tr><td>4</td><td>Chassis</td></tr></table>	Pin	Assignment	1	Chassis	2	Chassis	3	Chassis	4	Chassis	<table><tr><th>Pin</th><th>Assignment</th></tr><tr><td>1</td><td>Line</td></tr><tr><td>2</td><td>Line</td></tr><tr><td>3</td><td>Chassis</td></tr><tr><td>4</td><td>Chassis</td></tr></table>	Pin	Assignment	1	Line	2	Line	3	Chassis	4	Chassis	<table><tr><th>Pin</th><th>Assignment</th></tr><tr><td>1</td><td>Line</td></tr><tr><td>2</td><td>Line</td></tr><tr><td>3</td><td>Chassis</td></tr><tr><td>4</td><td>Chassis</td></tr></table>	Pin	Assignment	1	Line	2	Line	3	Chassis	4	Chassis	<table><tr><th>Pin</th><th>Assignment</th></tr><tr><td>1</td><td>Line</td></tr><tr><td>2</td><td>Line</td></tr><tr><td>3</td><td>Chassis</td></tr><tr><td>4</td><td>Line</td></tr></table>	Pin	Assignment	1	Line	2	Line	3	Chassis	4	Line
Pin	Assignment																																										
1	Chassis																																										
2	Chassis																																										
3	Chassis																																										
4	Chassis																																										
Pin	Assignment																																										
1	Line																																										
2	Line																																										
3	Chassis																																										
4	Chassis																																										
Pin	Assignment																																										
1	Line																																										
2	Line																																										
3	Chassis																																										
4	Chassis																																										
Pin	Assignment																																										
1	Line																																										
2	Line																																										
3	Chassis																																										
4	Line																																										
IP67	IP67	IP67	IP67																																								
• 60 / 70 mm ²	• 54 mm	• 65 mm (max)	• 73 mm																																								
• Ø 30 mm	• Ø 23 mm	• Ø 27 mm	• Ø 26 mm																																								
Order number: 001	Order number: 002	Order number: 004	Order number: 003																																								
* without copper jacket = 60 mm, with copper jacket = 70 mm																																											
DEUTSCH DT04-4P	DEUTSCH DT04-3P	Cable connection																																									
<table><tr><th>Pin</th><th>Assignment</th></tr><tr><td>1</td><td>Chassis</td></tr><tr><td>2</td><td>Line</td></tr><tr><td>3</td><td>Line</td></tr><tr><td>4</td><td>Chassis</td></tr></table>	Pin	Assignment	1	Chassis	2	Line	3	Line	4	Chassis	<table><tr><th>Pin</th><th>Assignment</th></tr><tr><td>1</td><td>Line</td></tr><tr><td>2</td><td>Line</td></tr><tr><td>3</td><td>Chassis</td></tr></table>	Pin	Assignment	1	Line	2	Line	3	Chassis	<table><tr><th>Cable</th><th>Assignment</th></tr><tr><td>white</td><td>Line</td></tr><tr><td>black</td><td>Chassis</td></tr></table>		Cable	Assignment	white	Line	black	Chassis																
Pin	Assignment																																										
1	Chassis																																										
2	Line																																										
3	Line																																										
4	Chassis																																										
Pin	Assignment																																										
1	Line																																										
2	Line																																										
3	Chassis																																										
Cable	Assignment																																										
white	Line																																										
black	Chassis																																										
IP67	IP67	IP67																																									
• 38 mm	• 38 mm	• 68 mm (20 mm band width)																																									
• Ø 23 mm	• Ø 23 mm	• cable length = 2 m																																									
Order number: 004	Order number: 005	Order number: 011																																									
Thread code: 41	Thread code: 03	Thread code: 04	Thread code: 09																																								
Thread code: 08	Thread code: 05	Thread code: 06	Thread code: 10																																								
Thread code: 11	Thread code: 07	Thread code: 12	Thread code: 13																																								
Thread code: 14	Thread code: 15	Thread code: 16	Thread code: 17																																								
Thread code: 18	Thread code: 19	Thread code: 20	Thread code: 21																																								
Thread code: 22	Thread code: 23	Thread code: 24	Thread code: 25																																								
Thread code: 26	Thread code: 27	Thread code: 28	Thread code: 29																																								
Thread code: 30	Thread code: 31	Thread code: 32	Thread code: 33																																								
Thread code: 34	Thread code: 35	Thread code: 36	Thread code: 37																																								
Thread code: 38	Thread code: 39	Thread code: 40	Thread code: 41																																								
Thread code: 42	Thread code: 43	Thread code: 44	Thread code: 45																																								
Thread code: 46	Thread code: 47	Thread code: 48	Thread code: 49																																								
Thread code: 50	Thread code: 51	Thread code: 52	Thread code: 53																																								
Thread code: 54	Thread code: 55	Thread code: 56	Thread code: 57																																								
Thread code: 58	Thread code: 59	Thread code: 60	Thread code: 61																																								
Thread code: 62	Thread code: 63	Thread code: 64	Thread code: 65																																								
Thread code: 66	Thread code: 67	Thread code: 68	Thread code: 69																																								
Thread code: 70	Thread code: 71	Thread code: 72	Thread code: 73																																								
Thread code: 74	Thread code: 75	Thread code: 76	Thread code: 77																																								
Thread code: 78	Thread code: 79	Thread code: 80	Thread code: 81																																								
Thread code: 82	Thread code: 83	Thread code: 84	Thread code: 85																																								
Thread code: 86	Thread code: 87	Thread code: 88	Thread code: 89																																								
Thread code: 90	Thread code: 91	Thread code: 92	Thread code: 93																																								
Thread code: 94	Thread code: 95	Thread code: 96	Thread code: 97																																								
Thread code: 98	Thread code: 99	Thread code: 100	Thread code: 101																																								
Thread code: 102	Thread code: 103	Thread code: 104	Thread code: 105																																								
Thread code: 106	Thread code: 107	Thread code: 108	Thread code: 109																																								
Thread code: 110	Thread code: 111	Thread code: 112	Thread code: 113																																								
Thread code: 114	Thread code: 115	Thread code: 116	Thread code: 117																																								
Thread code: 118	Thread code: 119	Thread code: 120	Thread code: 121																																								
Thread code: 122	Thread code: 123	Thread code: 124	Thread code: 125																																								
Thread code: 126	Thread code: 127	Thread code: 128	Thread code: 129																																								
Thread code: 130	Thread code: 131	Thread code: 132	Thread code: 133																																								
Thread code: 134	Thread code: 135	Thread code: 136	Thread code: 137																																								
Thread code: 138	Thread code: 139	Thread code: 140	Thread code: 141																																								
Thread code: 142	Thread code: 143	Thread code: 144	Thread code: 145																																								
Thread code: 146	Thread code: 147	Thread code: 148	Thread code: 149																																								
Thread code: 150	Thread code: 151	Thread code: 152	Thread code: 153																																								
Thread code: 154	Thread code: 155	Thread code: 156	Thread code: 157																																								
Thread code: 158	Thread code: 159	Thread code: 160	Thread code: 161																																								
Thread code: 162	Thread code: 163	Thread code: 164	Thread code: 165																																								
Thread code: 166	Thread code: 167	Thread code: 168	Thread code: 169																																								
Thread code: 170	Thread code: 171	Thread code: 172	Thread code: 173																																								
Thread code: 174	Thread code: 175	Thread code: 176	Thread code: 177																																								
Thread code: 178	Thread code: 179	Thread code: 180	Thread code: 181																																								
Thread code: 182	Thread code: 183	Thread code: 184	Thread code: 185																																								
Thread code: 186	Thread code: 187	Thread code: 188	Thread code: 189																																								
Thread code: 190	Thread code: 191	Thread code: 192	Thread code: 193																																								
Thread code: 194	Thread code: 195	Thread code: 196	Thread code: 197																																								
Thread code: 198	Thread code: 199	Thread code: 200	Thread code: 201																																								
Thread code: 202	Thread code: 203	Thread code: 204	Thread code: 205																																								
Thread code: 206	Thread code: 207	Thread code: 208	Thread code: 209																																								
Thread code: 210	Thread code: 211	Thread code: 212	Thread code: 213																																								
Thread code: 214	Thread code: 215	Thread code: 216	Thread code: 217																																								
Thread code: 218	Thread code: 219	Thread code: 220	Thread code: 221																																								
Thread code: 222	Thread code: 223	Thread code: 224	Thread code: 225																																								
Thread code: 226	Thread code: 227	Thread code: 228	Thread code: 229																																								
Thread code: 230	Thread code: 231	Thread code: 232	Thread code: 233																																								
Thread code: 234	Thread code: 235	Thread code: 236	Thread code: 237																																								
Thread code: 238	Thread code: 239	Thread code: 240	Thread code: 241																																								
Thread code: 242	Thread code: 243	Thread code: 244	Thread code: 245																																								
Thread code: 246	Thread code: 247	Thread code: 248	Thread code: 249																																								
Thread code: 250	Thread code: 251	Thread code: 252	Thread code: 253																																								
Thread code: 254	Thread code: 255	Thread code: 256	Thread code: 257																																								
Thread code: 258	Thread code: 259	Thread code: 260	Thread code: 261																																								
Thread code: 262	Thread code: 263	Thread code: 264	Thread code: 265																																								
Thread code: 266	Thread code: 267	Thread code: 268	Thread code: 269																																								
Thread code: 270	Thread code: 271	Thread code: 272	Thread code: 273																																								
Thread code: 274	Thread code: 275	Thread code: 276	Thread code: 277																																								
Thread code: 278	Thread code: 279	Thread code: 280	Thread code: 281																																								
Thread code: 282	Thread code: 283	Thread code: 284	Thread code: 285																																								
Thread code: 286	Thread code: 287	Thread code: 288	Thread code: 289																																								
Thread code: 290	Thread code: 291	Thread code: 292	Thread code: 293																																								
Thread code: 294	Thread code: 295	Thread code: 296	Thread code: 297																																								
Thread code: 298	Thread code: 299	Thread code: 300	Thread code: 301																																								
Thread code: 302	Thread code: 303	Thread code: 304	Thread code: 305																																								
Thread code: 306	Thread code: 307	Thread code: 308	Thread code: 309																																								
Thread code: 310	Thread code: 311	Thread code: 312	Thread code: 313																																								
Thread code: 314	Thread code: 315	Thread code: 316	Thread code: 317																																								
Thread code: 318	Thread code: 319	Thread code: 320	Thread code: 321																																								
Thread code: 322	Thread code: 323	Thread code: 324	Thread code: 325																																								
Thread code: 326	Thread code: 327	Thread code: 328	Thread code: 329																																								
Thread code: 330	Thread code: 331	Thread code: 332	Thread code: 333																																								
Thread code: 334	Thread code: 335	Thread code: 336	Thread code: 337																																								
Thread code: 338	Thread code: 339	Thread code: 340	Thread code: 341																																								
Thread code: 342	Thread code: 343	Thread code: 344	Thread code: 345																																								
Thread code: 346	Thread code: 347	Thread code: 348	Thread code: 349																																								
Thread code: 350	Thread code: 351	Thread code:																																									



See 221

Connection diagrams

Up to 100 VAC



For permanent operation on each connector

100 VAC 100 Hz



For permanent operation on each connector

Technical modifications and errors excepted.