

## KUEBLER - ABSOLUTE-CODED ANGULAR TRANSMITTER SENDIX 5868/5888, OPTICAL, CANOPEN, Ø58 MM SERIE 5868 CANOPEN





- Housing diameter Ø58 mm
- CANopen / CANopenLift
- High shock resistance
- High enclosure class

### PRODUCT DESCRIPTION

Sendix 5868/5888 is a multivariate fieldbus transmitter with profibus in robust design. Thanks to the construction of Safety-Lock™ as well as the fully cast housing, the sensor is able to handle even the more demanding applications where there are high demands on the sensor. The wide temperature range combined with the high enclosure class allows the sensor to be used outdoors as well as applications where large temperature changes occur. Sendix 5868/5888 has LED indication which facilitates diagnosis of the sensor and a set button that facilitates calibration.

Please refer to the image below for ordering information.

Order code	8.5868 . XXXXX . XXXX					
Shaft version	Type	a	b	c	d	e
<b>a</b> Flange						
1 = clamping flange, IP65 ø 58 mm [2.28"]						
3 = clamping flange, IP67 ø 58 mm [2.28"]						
2 = synchro flange, IP65 ø 58 mm [2.28"]						
4 = synchro flange, IP67 ø 58 mm [2.28"]						
5 = square flange, IP65 □ 63.5 mm [2.5"]						
7 = square flange, IP67 □ 63.5 mm [2.5"]						
<b>b</b> Shaft (ø x L), with flat						
1 = 6 x 10 mm [0.24 x 0.39"] <sup>1)</sup>						
2 = 10 x 20 mm [0.39 x 0.79"] <sup>2)</sup>						
3 = 1/4" x 7/8"						
4 = 3/8" x 7/8"						
<b>c</b> Interface / power supply						
2 = CANopen DS301 V4.02, 10 ... 30 V DC						
5 = CANopen DS301 V4.02, 10 ... 30 V DC with 2048 ppr incremental track (TTL-compatible) <sup>3)</sup>						
<b>d</b> Type of connection						
removable bus terminal cover						
1 = radial cable gland						
2 = 2 x or 3 x M12 connector, 5-pin						
Fixed connection without bus terminal cover						
A = radial cable, 2 m [6.56'] PVC						
B = radial cable, special length PVC *)						
E = 1 x radial M12 connector, 5-pin						
F = 2 x radial M12 connector, 5-pin						
I = 1 x radial M23 connector, 12-pin						
J = 2 x radial M23 connector, 12-pin						
K = 1 x Sub-D connector, 9-pin						
*) Available special lengths (connection type B): 3, 5, 8, 10, 15 m [9.84, 16.40, 26.25, 32.80, 49.21'] order code expansion .XXXX = length in dm ex.: 8.5868.112B.2123.0030 (for cable length 3 m)						
<b>e</b> Fieldbus profile						
212 = CANopen						
221 = CANlift DS417 V1.01						
<b>f</b> Options (service)						
2 = no options						
3 = SET button						
<b>Optional on request</b>						
- Ex 2/22 <sup>4)</sup>						
- surface protection salt spray tested						
- seawater resistant (stainless steel V4A)						
<b>Salt spray tested / stainless steel V4A as standard types (deliverable as from 1 unit)</b>						
 salt spray tested: 8.5868.3222.2122-C						
 stainless steel V4A: 8.5868.3222.2122-V4A						



Interface	Type of connection	Cable (shield) bus terminal cover with terminal lead										
		Bus OUT					Bus IN					
2.5	1	Signal	CAN_GND	CAN_L	CAN_H	0V	+V	0V	+V	CAN_L	CAN_H	CAN_GND
		Abbreviation	CG	CL	CH	0V	+V	0V	+V	CL	CH	CG
Interface	Type of connection	Cable (isolates arranged individually before initial start up)										
2.5	A, B	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Cable colour	Wh	Bk	YE	GN	GT					
Interface	Type of connection	2 x M12 connector (3 x M12 connector with interface 5)										
2.5	2,F	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus OUT				
		Pin	1	2	5	4	1					
5	2	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	3	2	5	4	1					
5	2	Signal	A	X	B	B	0V	Incremental track				
		Pin	1	2	3	4	5					
Interface	Type of connection	1 x M12 connector										
2.5	E	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	3	2	5	4	1					
Interface	Type of connection	2 x M12 connector										
2.5	F	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus OUT				
		Pin	10	12	2	7	8					
2.5	F	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	10	12	2	7	8					
Interface	Type of connection	1 x M12 connector										
2.5	I	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	10	12	2	7	8					
Interface	Type of connection	Sub-D connector										
2.5	K	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	6	9	2	7	3					

Interface	Type of connection	Cable (shield) bus terminal cover with terminal lead										
		Bus OUT					Bus IN					
2.5	1	Signal	CAN_GND	CAN_L	CAN_H	0V	+V	0V	+V	CAN_L	CAN_H	CAN_GND
		Abbreviation	CG	CL	CH	0V	+V	0V	+V	CL	CH	CG
Interface	Type of connection	Cable (isolates arranged individually before initial start up)										
2.5	A, B	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Cable colour	Wh	Bk	YE	GN	GT					
Interface	Type of connection	2 x M12 connector (3 x M12 connector with interface 5)										
2.5	2,F	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus OUT				
		Pin	1	2	5	4	1					
5	2	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	3	2	5	4	1					
5	2	Signal	A	X	B	B	0V	Incremental track				
		Pin	1	2	3	4	5					
Interface	Type of connection	1 x M12 connector										
2.5	E	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	3	2	5	4	1					
Interface	Type of connection	2 x M12 connector										
2.5	F	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus OUT				
		Pin	10	12	2	7	8					
2.5	F	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	10	12	2	7	8					
Interface	Type of connection	1 x M12 connector										
2.5	I	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	10	12	2	7	8					
Interface	Type of connection	Sub-D connector										
2.5	K	Signal	0V	+V	CAN_L	CAN_H	CAN_GND	Bus IN				
		Pin	6	9	2	7	3					