OEM Automatic Ltd
Address: Whiteacres, Whetstone Leicester, LE8 6ZG
0116 284 9900 | Orders@oem.co.uk | www.oem.co.uk

GSM-PRO2, GSM-PRO2E SIM BASED SMS & EMAIL REPORTING MODULE

4G GSM Reporting Modules

16368.2
GSM-PRO2, 3G GSM Module - ** Replaced by 16454.2 - 4G EU version **



- 4G Modems with OTA capabilities
- Two or Ten multifunction inputs and one count input as standard
- One or four relay outputs as standard
- Expandable IO
- Android and IOS Smartphone app, Web based Portal

PRODUCT DESCRIPTION

GSM-PRO2: THE PERFECT COMMUNICATOR

CONTA-CLIP's GSM-PRO2 is an easy-to-use SMS reporting for remote monitoring of equipment that can signal changes of inputs and outputs through text messaging and email.
4G as standard to give full global coverage including the EU, USA & Australia.

The GSM-PRO2 module informs you when your process has achieved a user-defined status or limit value. Digital and analogue inputs values can also be sent via e-mail or SMS (text message). The digital relay outputs can be switched using an SMS sent from selected users allowing the system to be monitored and controlled remotely. Android and iPhone apps are available to make the monitoring and control functions of the GSM-PRO2 modules even easier to operate. To further add to the flexibility, a new Web Portal CONTA-SUPERVISION is available and can work across all platforms.

The user-friendly browser-based programming software can be used to configure the module´s inputs and outputs and their required functions.

INPUT AND OUTPUT

The GSM-PRO2 modules are equipped with two multi-function inputs, one relay output and a pulse counter input which can process a maximum of 1000 pulses per second, so that for example a photovoltaic system or a kWh meter can be connected. The compact unit can alos be configured as a Modbus Slave device.
The GSMPRO2E has ten multifunction inputs, 4 relay outputs and a pulse counter input
Both modules have built in hours run timers that can be assign to both inputs and outputs.

EXPANSION MODULES

All the GSM-PRO2 modules also provide the option for expanding the number of available inputs and outputs. Up to 15 I/O expansion modules, in 4 different versions, can be controlled for each module. The built-in plug connector supplies power and control functionality for the modules. The expansion modules can also be configured with the user-friendly browser-based application.

OTA (OVER-THE-AIR) CAPABILITIES

In many systems or machines, some parameters or user entries may need to be changed after the installation is completed.
Whether you are adding a new phone number or email address of a new user, a new I/O setting,
a change in the module name or any other change: the settings on all GSM-PRO2 modules can easily be changed from remote locations around the world.

OTA FIRMWARE UPDATES

The GSM-PRO2 can also update its firmware using OTA.
So modules with different versions can always be kept up to date.

LOGGING FUNCTIONALITY

Is your process running optimally? What happened last week?
How many hours has the machine been running this week?
The extensive logging functionality of the GSM-PRO2 module
allows you to log events that have taken place at a facility or a machine over a defined period of time. The log files can be transferred to the PC using a USB cable. Or you can have the log files automatically sent to your e-mail address or displayed via a web-based portal.

LOGS

- Event - logs all communication of the module
- Analogue - logs the process values of the analogue inputs at selected time intervals
- Counter - Logs the time that an input or output is activated

SMARTPHONE APP

CONTA-CLIP's iPhone and Android smartphone apps for the GSM-PRO2 modules provide a simple and fast solution so that you can get an overview of each system and application. This app can show you the status of all inputs and outputs from one or more GSM-PRO2 modules. They also allow you a degree of control over the process. Module outputs can be controlled easily and directly using this app. The app´s buttons provide an intuitive control interface (for controlling a heater, motor, water pump, etc.).

WEB IOT PORTAL SOFTWARE CONTA-SUPERVISION

The GSM-PRO2, like most SMS modules, is often used as stand-alone units in the field. These modules are put to use at various remote locations even though they normally have configurations which are very similar. It is often quite helpful to have one overall view of the status of all modules used in the field. The new GSM-PRO2 web-based portal software from CONTA-CLIP offers you precisely this possibility. All modules in the field can now be easily monitored and run from a single local site or control panel.

The CONTA-SUPERVISION IoT portal can be opened in a web browser but is also available as an APP in the Google Play or Apple App store. Try the unlimited possibilities of the CONTA-SUPERVISION IoT portal for FREE . There will be a minimal annual cost in the future (around €99/year per Account), but two GSM-PRO2 modules can still use the CONTA-SUPERVISON IoT portal for FREE . An annual fee will be charged for more than two GSM-PRO2 modules.