

## NH FUSE-SWITCH-DISCONNECTORS SIZE 2

33602000

NH fuse switch-disconnector size 2, 400A

- Fast and safe conversion of the connection for top or bottom; the parts under voltage remain shock protected
- CrossLink® adapter technology
- Simple and safe clicking into place and making contact
- Safe connection through shock protection split into two
- For busbars 12, 15, 20, 25, 30 x 5, 10 and section busbars



### PRODUCT DESCRIPTION

### TECHNICAL DATA

Busbar size	12,20,30x10mm
Dimensions width x height x depth	210 x 288 x 145
Nominal socket current	400 A
Number of poles	3
Pack size	1
Rated insulation voltage Ui AC	800 V
Rated insulation voltage Ui DC	500
Rated surge voltage (UIMP)	6 kV
Rated voltage AC	690 V
Rated voltage DC	440 V
Utilization category AC (IEC 60947-3)	AC-23B (400V)
Weight	5220 g