

SWITCH DISCONNECTOR ACCESSORIES

0172595

Early Break Auxiliary Contact For 80A & 100A

- Terminal covers
- Auxillary contacts
- Handles
- Clutch drive & interlock kits
- IP65 sealing kits



PRODUCT DESCRIPTION

Accessories for switch disconnecter range.

- Junction blocks that snap onto switch body to terminate neutral or earth connections
- Auxillary block with N/C+N/O contacts - snap onto switch body for remote contactor switching
- Early break auxillary block - snap onto switch body for remote contactor switching
- Padlockable handles for screw or ø22mm hole mount in red/yellow or grey
- Handle & legend for screw or ø22mm hole mount in red/yellow
- Terminal covers
- Clutch drive kits in 3 options to accomodate different panel depths
- Door interlock shroud to ensure panel door can only be opened in OFF position
- IP65 gasket kits to increase front of panel protection from IP40 to IP65

TECHNICAL DATA

Connection stranded wire with ferrule max	2 x 2.5mm ²
Conventional free air thermal current I _{th}	10 A
Rated insulation voltage U _i	400 V
Rated operating current I _e (AC15/230V)	6 A
Rated operating current I _e (AC15/400V)	4 A
Rated uninterrupted current I _u	10 A
Short circuit current with fuse gI/gG (A)	10 A
Storage temperature max	70 °C
Storage temperature min	-30 °C
Temperature operational max	70 °C

Temperature operational min	-30 °C
Type	Auxiliary contact

