

GSM-PRO2, GSM-PRO2E

16368.2

GSM-PRO2, 3G GSM Module - ** Replaced by 16454.2

- 4G EU version **

- 4G Modems with OTA capabilities
- Two or Ten multifunction inputs and one count input as standard
- One or four relay outputs as standard
- Expandable IO
- Android and IOS Smartphone app, Web based Portal



PRODUCT DESCRIPTION

GSM-PRO2: THE PERFECT COMMUNICATOR

CONTA-CLIP's GSM-PRO2 is an easy-to-use SMS reporting for remote monitoring of equipment that can signal changes of inputs and outputs through text messaging and email.

4G as standard to give full global coverage including the EU, USA & Australia.

The GSM-PRO2 module informs you when your process has achieved a user-defined status or limit value. Digital and analogue inputs values can also be sent via e-mail or SMS (text message). The digital relay outputs can be switched using an SMS sent from selected users allowing the system to be monitored and controlled remotely. Android and iPhone apps are available to make the monitoring and control functions of the GSM-PRO2 modules even easier to operate.

To further add to the flexibility, a new Web Portal CONTA-SUPERVISION is available and can work across all platforms.

The user-friendly browser-based programming software can be used to configure the module's inputs and outputs and their required functions.

INPUT AND OUTPUT

The GSM-PRO2 modules are equipped with two multi-function inputs, one relay output and a pulse counter input which can process a maximum of 1000

pulses per second, so that for example a photovoltaic system or a kWh meter can be connected. The compact unit can also be configured as a Modbus Slave device.

The GSM-PRO2E has ten multifunction inputs, 4 relay outputs and a pulse counter input

Both modules have built-in hours run timers that can be assigned to both inputs and outputs.

EXPANSION MODULES

All the GSM-PRO2 modules also provide the option for expanding the number of available inputs and outputs. Up to 15 I/O expansion modules, in 4 different versions, can be controlled for each module. The built-in plug connector supplies power and control functionality for the modules. The expansion modules can also be configured with the user-friendly browser-based application.

OTA (OVER-THE-AIR) CAPABILITIES

In many systems or machines, some parameters or user entries may need to be changed after the installation is completed.

Whether you are adding a new phone number or email address of a new user, a new I/O setting,

a change in the module name or any other change: the settings on all GSM-PRO2 modules can easily be changed from remote locations around the world.

OTA FIRMWARE UPDATES

The GSM-PRO2 can also update its firmware using OTA.

So modules with different versions can always be kept up to date.

LOGGING FUNCTIONALITY

Is your process running optimally? What happened last week?

How many hours has the machine been running this week?

The extensive logging functionality of the GSM-PRO2 module

allows you to log events that have taken place at a facility or a machine over a defined period of time. The log files can be transferred to the PC using a USB cable. Or you can have the log files automatically sent to your e-mail address or displayed via a web-based portal.

LOGS

- Event - logs all communication of the module
- Analogue - logs the process values of the analogue inputs at selected time intervals
- Counter - Logs the time that an input or output is activated

SMARTPHONE APP

CONTA-CLIP's iPhone and Android smartphone apps for the GSM-PRO2 modules provide a simple and fast solution so that you can get an overview of each system and application. This app can show you the status of all inputs and outputs from one or more GSM-PRO2 modules. They also allow you a degree of control over the process. Module outputs can be controlled easily and directly using this app. The app's buttons provide an intuitive control interface (for controlling a heater, motor, water pump, etc.).

WEB IOT PORTAL SOFTWARE CONTA-SUPERVISION

The GSM-PRO2, like most SMS modules, is often used as stand-alone units in the field. These modules are put to use at various remote locations even though they normally have configurations which are very similar. It is often quite helpful to have one overall view of the status of all modules used in the field. The new GSM-PRO2 web-based portal software from CONTA-CLIP offers you precisely this possibility. All modules in the field can now be easily monitored and run from a single local site or control panel.

The CONTA-SUPERVISION IoT portal can be opened in a web browser but is also available as an APP in the Google Play or Apple App store. Try the unlimited possibilities of the CONTA-SUPERVISION IoT portal for FREE. As of January 1, 2023, two GSM-PRO2(E) modules can still use the CONTA-SUPERVISION IoT portal for FREE. An annual fee will be charged for more than two GSM-PRO2(E) modules.

TECHNICAL DATA

GENERAL DATA

Number of inputs	2
Number of outputs	1
Supply voltage	10-30V dc
Current consumption	275 mA @ 24V dc
Mounting	TS 35 and direct mount

GPS	No
Electromagnetic compatibility	EN55011, EN61326-1
Operating temperature from	-20 °C
Operating temperature to	60 °C

DIMENSIONS

Length	88 mm
Width	36 mm
Height	77 mm
Weight	135 g

INPUTS

Input resistance U / I	80K / 500Ω
Input signal U / I max	30 V / -
Threshold digital inputs	Low <3, High >6V
Minimum pulse duration	500 ms
Resolution I (0-20 mA)	40 μA / ± (40 μ + 0,3%)
Resolution U (0-10 V dc)	20mV / ±(20mV+0,3%)
Counter input (pull-down)	1000 pulses/s max. Pulldown res. 24 kOhm

OUTPUTS

Relay contact	1 CO
Contact material	AgNi 90/10
Switching capacity max	1200 VA
Rated V ac / switching V ac max	250 / 250 V ac
Continuous current max / Inrush current max	5 / 5 A
Mechanical life hours	15x10 ⁶
Electrical life in hours (AC1)	1,5x10 ⁵

CONNECTIONS



Connection type	Screw
Cross section single wire from	0,2 mm ²
Cross section single wire to	4 mm ²
Stripping length	6 mm
Torque	0,4 Nm
Number of ext. modules max	15

GSM/GPS DATA

2G	Quad-band GSM bands: 850, 900, 1800 and 1900 MHz
3G	Five-band UMTS (WCDMA/FDD) bands: 800, 850, 900, 1800, 1900 and 2100 MHz
SIM card	Nano-SIM
Antenna GSM	50 Ohm, SMA-plug

ADDITIONAL DATA

DIN-VDE Spec	LVD 2014/35/EC, EN 50178. EMC 2014/30/EC, EN 61326-1
IP class	IP20
Relative humidity max	80 %
Pack size	1
Country of origin	NL
Tariff code	85176990
Frequency spectrum	ETSI EN 301-511 V9.0.2



LOGIN

REGISTER

Conta-SuperVision

[Forgot Password?](#)

LOGIN