

# **DATASENSING VISION SENSOR DATAVS2 AOR**

DATAVS2-06DEAOR  
Vision Sensor, 6mm lens, ADV Object recognition, Red LED

- 360° pattern recognition
- 8 different controls
- Memory for up to 20 different inspections
- 4 outputs



## **PRODUCT DESCRIPTION**

DataVS2 is a series of Vision sensors for flexible solutions for machine applications.

The sensor is complete with optics, red LED lighting and electronics in a compact housing. The parameters in the sensor are set via PC through Ethernet communication. The software comes with the sensor and is developed to lead the user step by step through parameter setting. DataVS2 is available in three different versions with different control instruments.

Advanced Object recognition AOR - Has a control instrument for 360° pattern recognition.

.Logic functions for that are connected between different control instruments and outputs such as: AND, OR, NOT, NAND, NOR etc.

## **TECHNICAL DATA**

Digital interface	Ethernet 10/100 Mbs (4-pole M12 -connector)
Electrical connection	M12 4-pole D-coded, M12 8-pin connector
Frame rate	60
IP class	IP50
Lens material	ABS plastic
Material protection	Aluminium
Optics	6mm integrated lens
Output	4xPNP
Output current max	0,1 A
Power consumption max	0,1 A
Resolution	640x480 (VGA)
Temperature operational max	50 °C
Temperature operational min	-10 °C

Voltage dc max 24 V

Voltage dc min 24 V

Voltage tolerance 10%

The Advanced Object Recognition (AOR) models integrate new important functionalities, including:



**360° Pattern Match Locator**  
Object detection independent from rotations.




**Logical tools**  
Possibility to combine the results of the single tools through logical operator (AND, OR, NOT, etc.)




**Advanced Ethernet**  
Current inspection results available also on Ethernet communication.



**Speed-up**  
High execution speed thanks to the management of reduced resolution and TURBO mode



### 360° Pattern match



### Step 1: Image Setup



The first step consists in connecting the sensor and configuring the image quality parameters. When the desired results are obtained, the user can memorise the image that will be used as a template during sensor functioning.

### Step 2: Teach



The second step establishes the acceptance criteria to distinguish objects from wastes. One or more controls can be selected according to the task to carry-out.

### Step 3: Run



The third step configures the sensor digital outputs, simulates sensor functioning on the PC to verify the controls chosen and activates the operating phase on the sensor using the PC only to control the diagnostics.



### M12 4-pole Ethernet

PIN 1 = white/orange = RX+  
PIN 2 = white/green = TX+  
PIN 3 = orange = RX-  
PIN 4 = green = TX-

### M12 8-pole (power supply and I/O)

PIN 1 = white = digital input 1  
PIN 2 = brown = +24 VDC  
PIN 3 = green = STROBE for external illuminator  
PIN 4 = yellow = output 1  
PIN 5 = grey = output 2  
PIN 6 = pink = output 3  
PIN 7 = blue = GND  
PIN 8 = red = external trigger

