
### **OEM Automatic Ltd**

Address: Whiteacres, Whetstone Leicester, LE8 6ZG 0116 284 9900 | Orders@oem.co.uk | www.oem.co.uk

# **CROUZET - SYNCHRONOUS MOTORS**

823400XX Synchronous Motor 0.16W 24?240Vac 600rpm 2.5mNm 1-direction

- Single phase 24V→230V / 50Hz
- 0.2→3W, 2.5→106mNm, 250→600rpm
- · Constant speed independant of load
- · Short start & stop times
- Single direction & reversible options



### PRODUCT DESCRIPTION

The Crouzet synchronous motor is a small, compact motor with precise speed and short start and stop times.

A Synchronous motor is characterised by a constant speed of rotation which isindependent of the load but linked to the supply frequency.

A synchronous motor maintains its speed of rotation until an overload occurs. When overload occurs, the motor loses synchronisation, ie. it stops and develops an oscillation (vibration).

Available in single direction clockwise, anti-clockwise, or reversible.

No capacitor required on single direction motors.

Motors for other voltages than 230 V ac/50 Hz are available.


## **TECHNICAL DATA**

Diameter	47 mm
IP class	IP30
Length	17 mm
Max. torque	0.0033
Nominal speed	600 rpm
Nominal torque	0.0025
Power	0.16 W
Shaft diameter	2 mm
Supply voltage	230 V AC
Weight	0.11 kg



## Dimensions

#### 82 340 0



 $\bigcirc\hspace{-0.07cm}\bigcirc\hspace{-0.07cm} 3$  fixing holes ØM2 at 120  $^{\circ}$  on r=19.5 max. depth 2.4 mm