OEM Automatic Ltd
Address: Whiteacres, Whetstone Leicester, LE8 6ZG
0116 284 9900 | Orders@oem.co.uk | www.oem.co.uk

RK SAFE BOX TS35/100

17690.4
RK-Safe-Box TS 35/100 BK



- Securable cover to prevent access
- Designed for use on CT Link assemblies
- Compatable with PTK disconnect range

PRODUCT DESCRIPTION

Using their innovative terminal block housing, RK Safe-Box, Contaclip offer you a quick and easy protection for terminal blocks, electronic transformers etc., which are installed on mounting rails. The Safe-Box effectively prevents the unauthorised operation of converter terminals or the changing of the wiring particularly in the pre-meter area of power distribution systems. The side panels are directly on the mounting plate and totally enclose the components or assemblies which are to be protected. The wire-feed through the walls of the box simplifies the wiring and makes the subsequent manipulation of the clamp connections with a closed box impossible. Without the transparent lid, the internal dimensions of the box can be extended by 16 mm using the built-in sliding mechanism. This makes maintenance work or the exchange of terminals or components much easier.

Features:

- Quick and easy to install on TS 35 DIN mounting rails
- Highest mechanical attachment to the mounting rail
- When fitted, it cannot be unlocked from the mounting rail, nor can it be pulled off
- Three seal fitting locations are available
- Transparent lid
- Any alterations are immediately detectable
- The sliding mechanism of the two housing halves means that the installed components are more easily accessible during maintenance.

TECHNICAL DATA

GENERAL DATA

Colour	Black

DIMENSIONS

Length	91 mm
Width	101.3 mm
Height TS 35/7.5	68.5 mm
Height TS 15/5.5	76 mm
IP class	IP20

MATERIALS

Material	Polyamide 6.6
Flammability class	UL94-V0
Operating temperature from	-40 °C
Operating temperature to	120 °C

ADDITIONAL DATA

Tariff code	85369010
Country of origin	DE
Weight	77 g
Pack size	1