

0116 284 9900 | Orders@oem.co.uk | www.oem.co.uk

### VARIOLINE LAMP WITH SOCKET LED 121/122 - OBSOLETE - NEW RANGE **COMING SOON**

Varioline

12224.0-00 OBSOLETE - LED 122 120V AC, door switch, screw fixing, USA/Canada socket

OBSOLETE

- FOR LED LIGHT USE LED 025
- FOR SOCKETS USE SD 035





#### **PRODUCT DESCRIPTION**

LED 121/122 Range is now Obsolete - Stego has a New Range coming Mid 2024

# **TECHNICAL DATA**

#### **GENERAL DATA**

Width

Height

Mounting	Screw fixing
Nominal voltage	120 V AC
Activation	Door switch
Connection type	3-pole plug with snap lock
Socket	USA/CA
Nominal socket current	15 A
Light source	LED
Luminance	1.080 Lm/1.730 Lm
Life span	60,000h at +20°C
DIMENSIONS	
Length	700 mm

100 mm

44 mm

# **ELECTRICAL SPECIFICATION**


Frequency	50/60 Hz
Power consumption	16 W

### **SAFETY & APPROVALS**

Protection class	I (earthed)
IP class	IP20
Approvals	CE, RoHS
Approvals pending	UL


# **MATERIALS - CONDITIONS**

Material of body	Plastic
Colour	Translucent/White
Operational temperature	-30°C +40°C
Storage temperature	-40°C +85°C
Operating humidity	< 90% RH
Humidity storage	<90% RH
Voltage min	110 V ac
Voltage max	130 V ac
Weight	0.4 kg





View of screw fixing



LED 121 (Size 1) LED 122 (Size 2) L1 = 500 mm L2 = 475 mm

L1 = 700 mm L2 = 675 mm

