## VARIOLINE LAMP WITH SOCKET LED 121/122 - OBSOLETE - NEW RANGE COMING SOON

Varioline

12115.0-30 OBSOLETE - LED 121 220-240V AC,PIR sensor,magnet fixing, Italy socket

• OBSOLETE

- FOR LED LIGHT USE LED 025
- FOR SOCKETS USE SD 035





#### PRODUCT DESCRIPTION

LED 121/122 Range is now Obsolete - Stego has a New Range coming Mid 2024

# **TECHNICAL DATA**

#### **GENERAL DATA**

Mounting	Magnetic mount
Nominal voltage	220-240 V AC
Activation	IR sensor
Connection type	3-pole plug with snap lock
Socket	IT
Nominal socket current	16 A
Light source	LED
Luminance	1.080 Lm/1.730 Lm
Life span	60,000h at +20°C
DIMENSIONS	

Length	500 mm
Width	100 mm
Height	44 mm

# **ELECTRICAL SPECIFICATION**

Frequency	50/60 Hz
Power consumption	11 W

## **SAFETY & APPROVALS**


Protection class	I (earthed)
IP class	IP20
Approvals	CE, RoHS
Approvals pending	VDE

#### **MATERIALS - CONDITIONS**

Material of body	Plastic
Colour	Translucent/White
Operational temperature	-30°C +40°C
Storage temperature	-40°C +85°C
Operating humidity	< 90% RH
Humidity storage	<90% RH

## **ADDITIONAL DATA**

Weight	0,4 kg
Voltage max	265 V ac
Voltage min	200 V ac



L2 = 475 mm

