# VARIOLINE LAMP WITH SOCKET LED 121/122 - OBSOLETE - NEW RANGE COMING SOON

Varioline

12223.0-30 OBSOLETE - LED 122 220-240V AC, door switch, magnet fixing, UK/Ireland socket

- OBSOLETE
- FOR LED LIGHT USE LED 025
- FOR SOCKETS USE SD 035





#### PRODUCT DESCRIPTION

LED 121/122 Range is now Obsolete - Stego has a New Range coming Mid 2024

## **TECHNICAL DATA**

#### **GENERAL DATA**

Mounting	Magnetic mount
Nominal voltage	220-240 V AC
Activation	Door switch
Connection type	3-pole plug with snap lock
Socket	UK/IE
Nominal socket current	13 A
Light source	LED
Luminance	1.080 Lm/1.730 Lm
Life span	60,000h at +20°C

#### **DIMENSIONS**

Length	700 mm
Width	100 mm
Height	44 mm

## **ELECTRICAL SPECIFICATION**

Frequency	50/60 Hz
Power consumption	16 W

## **SAFETY & APPROVALS**


Protection class	I (earthed)
IP class	IP20
Approvals	CE, RoHS
Approvals pending	VDE


## **MATERIALS - CONDITIONS**


Material of body	Plastic
Colour	Translucent/White
Operational temperature	-30°C +40°C
Storage temperature	-40°C +85°C
Operating humidity	< 90% RH
Humidity storage	<90% RH

### **ADDITIONAL DATA**

Weight	0,4 kg
Voltage max	265 V ac
Voltage min	200 V ac







LED 121 (Size 1) L1 = 500 mm L2 = 475 mm LEO 122 (Size 2) L1 = 700 mm L2 = 675 mm

